



MCB group sizes SNEP[®] AARI

	Length [mm]	Power	Control	C10	C13	C16	B10	B13	B16	Optics	Modules
Aari6x6	595x595	HE	On/Off	28	36	45	17	22	27	M1, S0, S0R	1x
Aari6x6	595x595	HE	DALI	31	40	50	18	24	30	M1, S0, S0R	1x
Aari6x6	595x595	HE	ActiveAhead gen2 with sensor	34	45	56	20	26	33	M1, S0, S0R	1x
Aari6x6	595x595	HE	Casambi	34	45	56	20	26	33	M1, S0, S0R	1x
Aari6x6	595x595	HO	On/Off	22	29	36	13	17	21	M1, S0, S0R	1x
Aari6x6	595x595	HO	DALI	18	24	30	11	14	18	M1, S0, S0R	1x
Aari6x6	595x595	HO	ActiveAhead gen2 with sensor	19	25	31	11	14	18	M1, S0, S0R	1x
Aari6x6	595x595	HO	Casambi	19	25	31	11	14	18	M1, S0, S0R	1x
Aari6x6	595x595	HO	DALI DT8 (TW)	39	50	62	24	31	39	M1, S0, S0R	1x
Aari6x6	595x595	HO	Casambi	39	50	62	24	31	39	M1, S0, S0R	1x
Aari6x6	595x595	HE	On/Off	18	24	30	11	14	18	M1, S0, S0R	2x
Aari6x6	595x595	HE	DALI	19	25	31	11	14	18	M1, S0, S0R	2x
Aari6x6	595x595	HO	On/Off	13	17	22	8	10	13	M1, S0, S0R	2x
Aari6x6	595x595	HO	DALI	13	17	21	7	10	12	M1, S0, S0R	2x

The announced circuit breaker group sizes are presenting the lower value from the inrush current and continuous load values. When designing actual group sizes one need to take into account at least the following: cabling, MCB installation environment and the loading of the MCB. Purso Oy is not responsible for the actual group sizes.