



## MCB group sizes SNEP® LX

	Length [mm]	Power	Control	C10	C13	C16	B10	B13	B16	Optics
LX	1160	LE	On/Off	27	35	44	16	21	26	UDW80, UDW50, UDB80, UDB50
LX	1160	LE	DALI	21	28	35	13	17	21	UDW80, UDW50, UDB80, UDB50
LX	1160	LE	Pull Switch (dimmmable with pull cord)	21	28	35	13	17	21	UDW80, UDW50, UDB80, UDB50
LX	1160	LE	ActiveAhead gen2 with sensor	34	45	56	20	26	33	UDW80, UDW50, UDB80, UDB50
LX	1160	LE	Casambi without sensor	34	45	56	20	26	33	UDW80, UDW50, UDB80, UDB50
LX	1160	LO1	On/Off	16	21	26	10	13	16	UDW80, UDW50, UDB80, UDB50
LX	1160	LO1	DALI	19	25	31	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO1	Pull Switch (dimmmable with pull cord)	19	25	31	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO1	ActiveAhead gen2 with sensor	19	25	31	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO1	Casambi without sensor	19	25	31	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO2	On/Off	16	21	26	9	12	15	UDW80, UDW50, UDB80, UDB50
LX	1160	LO2	DALI	18	24	30	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO2	Pull Switch (dimmmable with pull cord)	18	24	30	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO2	ActiveAhead gen2 with sensor	18	24	30	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO2	Casambi without sensor	18	24	30	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO	Casambi Tunable White	18	24	30	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO	DALI	18	24	30	11	14	18	UDW80, UDW50, UDB80, UDB50
LX	1160	LO2	Dual channel DALI for separate up and down light	15	20	25	9	12	15	UDW80, UDW50, UDB80, UDB50
LX	1160	LO2	Casambi separate up- and downlight control	15	20	25	9	12	15	UDW80, UDW50, UDB80, UDB50
LX	1160	LE	On/Off	16	21	26	10	13	16	DW80, DW50, DB80, DB50
LX	1160	LE	DALI	21	28	35	13	17	21	DW80, DW50, DB80, DB50
LX	1160	LE	Pull Switch (dimmmable with pull cord)	21	28	35	13	17	21	DW80, DW50, DB80, DB50
LX	1160	LE	ActiveAhead gen2 with sensor	34	45	56	20	26	33	DW80, DW50, DB80, DB50
LX	1160	LE	Casambi without sensor	34	45	56	20	26	33	DW80, DW50, DB80, DB50
LX	1160	LO	On/Off	16	21	26	9	12	15	DW80, DW50, DB80, DB50
LX	1160	LO	DALI	18	24	30	11	14	18	DW80, DW50, DB80, DB50
LX	1160	LO	Pull Switch (dimmmable with pull cord)	18	24	30	11	14	18	DW80, DW50, DB80, DB50
LX	1160	LO	ActiveAhead gen2 with sensor	18	24	30	11	14	18	DW80, DW50, DB80, DB50
LX	1160	LO	Casambi without sensor	18	24	30	11	14	18	DW80, DW50, DB80, DB50
LX	1160	LO	Casambi Tunable White	18	24	30	11	14	18	DW80, DW50, DB80, DB50
LX	1160	LO	DALI	18	24	30	11	14	18	DW80, DW50, DB80, DB50
LX	1160	HE	DALI Tunable White	39	50	62	24	31	39	UDW80, UDW50, UDB80, UDB50

	Length [mm]	Power	Control	C10	C13	C16	B10	B13	B16	Optics
LX	1160	HE	Casambi Tunable White	39	50	62	24	31	39	UDW80, UDW50, UDB80, UDB50
LX	1160	HE		39	50	62	24	31	39	UDW80, UDW50, UDB80, UDB50
LX	1160	HO	DALI Tunable White	15	20	25	9	12	15	UDW80, UDW50, UDB80, UDB50
LX	1160	HO	Casambi Tunable White	15	20	25	9	12	15	UDW80, UDW50, UDB80, UDB50
LX	1160	HO		15	20	25	9	12	15	UDW80, UDW50, UDB80, UDB50
LX	1160	HE	DALI Tunable White	39	50	62	24	31	39	DW80, DW50, DB80, DB50
LX	1160	HE	Casambi Tunable White	39	50	62	24	31	39	DW80, DW50, DB80, DB50
LX	1160	HE		39	50	62	24	31	39	DW80, DW50, DB80, DB50

The announced circuit breaker group sizes are presenting the lower value from the inrush current and continuous load values. When designing actual group sizes one need to take into account at least the following: cabling, MCB installation environment and the loading of the MCB. Purso Oy is not responsible for the actual group sizes.