



MCB group sizes SNEP[®] Advanced panel

	Length [mm]	Power	Control	C10	C13	C16	B10	B13	B16
Adv 6x6	595x595	HE	On/Off	18	23	28	11	14	17
Adv 6x6	595x595	HE	DALI	21	30	36	13	18	22
Adv 6x6	595x595	HE	Casambi	23	31	38	14	19	23
Adv 6x6	595x595	HE	DALI Tunable White	16	21	26	10	13	16
Adv 6x6	595x595	HE	Casambi Tunable White	16	21	26	10	13	16
Adv 6x6	595x595	HE	On/Off	16	21	26	10	13	16
Adv 6x6	595x595	HE	DALI	13	18	21	8	11	13
Adv 6x6	595x595	HE	Casambi	13	18	21	8	11	13
Adv 6x6	595x595	NM	On/Off	18	23	28	11	14	17
Adv 6x6	595x595	NM	DALI	21	30	36	13	18	22
Adv 6x6	595x595	NM	Casambi	23	31	38	14	19	23
Adv 6x6	595x595	NM	DALI Tunable White	16	21	26	10	13	16
Adv 6x6	595x595	NM	Casambi Tunable White	16	21	26	10	13	16
Adv 6x6	595x595	NM	On/Off	16	21	26	10	13	16
Adv 6x6	595x595	NM	DALI	13	18	21	8	11	13
Adv 6x6	595x595	NM	Casambi	13	18	21	8	11	13
Adv 6x6	595x595	HO	On/Off	18	23	28	11	14	17
Adv 6x6	595x595	HO	DALI	21	30	36	13	18	22
Adv 6x6	595x595	HO	Casambi	23	31	38	14	19	23
Adv 6x6	595x595	HO	DALI Tunable White	16	21	26	10	13	16
Adv 6x6	595x595	HO	Casambi Tunable White	16	21	26	10	13	16
Adv 6x6	595x595	HO	On/Off	16	21	26	10	13	16
Adv 6x6	595x595	HO	DALI	13	18	21	8	11	13
Adv 6x6	595x595	HO	Casambi	13	18	21	8	11	13
Adv 3x12	295x1195	HE	On/Off	18	23	28	11	14	17
Adv 3x12	295x1195	HE	DALI	21	30	36	13	18	22
Adv 3x12	295x1195	HE	Casambi	23	31	38	14	19	23
Adv 3x12	295x1195	HE	On/Off	16	21	26	10	13	16
Adv 3x12	295x1195	HE	DALI	13	18	21	8	11	13
Adv 3x12	295x1195	HE	Casambi	13	18	21	8	11	13
Adv 3x12	295x1195	NM	On/Off	18	23	28	11	14	17
Adv 3x12	295x1195	NM	DALI	21	30	36	13	18	22

	Length [mm]	Power	Control	C10	C13	C16	B10	B13	B16
Adv 3x12	295x1195	NM	Casambi	23	31	38	14	19	23
Adv 3x12	295x1195	NM	On/Off	16	21	26	10	13	16
Adv 3x12	295x1195	NM	DALI	13	18	21	8	11	13
Adv 3x12	295x1195	NM	Casambi	13	18	21	8	11	13
Adv 3x12	295x1195	HO	On/Off	18	23	28	11	14	17
Adv 3x12	295x1195	HO	DALI	21	30	36	13	18	22
Adv 3x12	295x1195	HO	Casambi	23	31	38	14	19	23
Adv 3x12	295x1195	HO	On/Off	16	21	26	10	13	16
Adv 3x12	295x1195	HO	DALI	13	18	21	8	11	13
Adv 3x12	295x1195	HO	Casambi	13	18	21	8	11	13

The announced circuit breaker group sizes are presenting the lower value from the inrush current and continuous load values. When designing actual group sizes one need to take into account at least the following: cabling, MCB installation environment and the loading of the MCB. Purso Oy is not responsible for the actual group sizes.