



MCB group sizes SNEP[®] MODE CT

	Length [mm]	Power	Control	C10	C13	C16	B10	B13	B16
CT02	615	XE	On/off	13	17	22	8	10	13
CT02	615	XE	DALI	13	17	21	7	10	12
CT02	615	XE	Industrial On/off	11	14	18	11	14	18
CT02	615	XE	Industrial DALI	11	14	18	11	14	18
CT02	615	XO	On/off	11	15	19	7	9	11
CT02	615	XO	DALI	12	16	20	7	9	12
CT02	615	XO	Industrial On/off	11	14	18	11	14	18
CT02	615	XO	Industrial DALI	11	14	18	10	12	16
CT02	615	XT	Industrial On/off	11	14	18	11	14	18
CT02	615	XT	Industrial DALI	11	14	18	10	12	16
CT04	1180	HE	On/off	11	14	18	7	9	11
CT04	1180	HE	DALI	11	14	18	7	9	12
CT04	1180	HE	Industrial On/off	11	14	18	11	14	18
CT04	1180	HE	Industrial DALI	11	14	18	10	12	16
CT04	1180	HE1	On/off	13	17	20	12	16	20
CT04	1180	HE1	DALI	13	17	20	12	16	20
CT04	1180	HE1	Industrial On/off	13	17	20	12	16	20
CT04	1180	HE1	Industrial DALI	13	17	20	12	16	20
CT04	1180	HO	2 x On/Off ECG	6	8	11	4	5	6
CT04	1180	HO	2 x DALI ECG	6	8	10	3	5	6
CT04	1180	HO	2 x Industrial On/Off ECG	6	8	10	5	7	9
CT04	1180	HO	2 x Industrial DALI ECG	6	8	10	5	6	8
CT04	1180	XO	2 x On/Off ECG	5	7	9	3	4	5
CT04	1180	XO	2 x DALI ECG	5	7	9	3	4	6
CT04	1180	XO	2 x Industrial On/Off ECG	5	7	9	5	7	9
CT04	1180	XO	2 x Industrial DALI ECG	5	7	9	5	7	9
CT04	1180	XT	2 x Industrial On/Off ECG	5	7	9	5	7	9
CT04	1180	XT	2 x Industrial DALI ECG	5	7	9	5	6	8
CT04	1180	XO2	2 x On/Off ECG	6	8	10	6	8	10
CT04	1180	XO2	2 x DALI ECG	6	8	10	6	8	10
CT04	1180	XO2	2 x Industrial On/Off ECG	6	8	10	6	8	10
CT04	1180	XO2	2 x Industrial DALI ECG	6	8	10	6	8	10
CT02	615	XP	On/off	9	12	15	6	8	11
CT02	615	XP	DALI	9	12	15	9	11	13
CT02	615	XP	Industrial On/off	9	12	15	6	8	11
CT02	615	XP	Industrial DALI	9	12	15	9	11	13
CT04	1180	HP	On/off	9	12	15	6	8	11
CT04	1180	HP	DALI	9	12	15	9	11	13
CT04	1180	HP	Industrial On/off	9	12	15	6	8	11
CT04	1180	HP	Industrial DALI	9	12	15	9	11	13

The announced circuit breaker group sizes are presenting the lower value from the inrush current and continuous load values. When designing actual group sizes one need to take into account at least the following: cabling, MCB installation environment and the loading of the MCB. Purso Oy is not responsible for the actual group sizes.